

<b>REPORT DOCUMENTATION PAGE</b>			Form Approved OMB NO. 0704-0188	
Public Reporting burden for this collection of information is estimated to average 1 hour per response, including the time for reviewing instructions, searching existing data sources, gathering and maintaining the data needed, and completing and reviewing the collection of information. Send comment regarding this burden estimate or any other aspect of this collection of information, including suggestions for reducing this burden, to Washington Headquarters Services, Directorate for Information Operations and Reports, 1215 Jefferson Davis Highway, Suite 1204, Arlington, VA 22202-4302, and to the Office of Management and Budget, Paperwork Reduction Project (0704-0188), Washington, DC 20503.				
1. AGENCY USE ONLY (Leave Blank)		2. REPORT DATE June 6, 2003		3. REPORT TYPE AND DATES COVERED Technical Report No: MS-CIS-03-03, 2003
4. TITLE AND SUBTITLE From Nonlinear to Hamiltonian via Feedback			5. FUNDING NUMBERS DAAD19-02-1-0383	
6. AUTHOR(S) Paulo Tabuada and George J. Pappas				
7. PERFORMING ORGANIZATION NAME(S) AND ADDRESS(ES) Regents of the University of California c/o Sponsored Projects Office 336 Sproul Hall Berkeley, CA 94720-5940			8. PERFORMING ORGANIZATION REPORT NUMBER	
9. SPONSORING / MONITORING AGENCY NAME(S) AND ADDRESS(ES)  U. S. Army Research Office P.O. Box 12211 Research Triangle Park, NC 27709-2211			10. SPONSORING / MONITORING AGENCY REPORT NUMBER 35873-MA-MUR •10	
11. SUPPLEMENTARY NOTES The views, opinions and/or findings contained in this report are those of the author(s) and should not be construed as an official Department of the Army position, policy or decision, unless so designated by other documentation.				
12 a. DISTRIBUTION / AVAILABILITY STATEMENT  Approved for public release; distribution unlimited.			12 b. DISTRIBUTION CODE	
13. Abstract Mechanical control systems are a very important class of nonlinear control systems. They possess a rich mathematical structure which can be extremely important for the solution of various control problems. In this paper we expand the applicability of design methodologies developed for mechanical control systems by logically rendering nonlinear control systems, mechanical by a proper choice of feedback. In particular, we characterize control systems which can be transformed to Hamiltonian control systems by a local feedback transformation.				
14. SUBJECT TERMS Nonlinear mechanical control systems, Hamiltonian Control Systems			15. NUMBER OF PAGES xxxx	
			16. PRICE CODE	
17. SECURITY CLASSIFICATION OR REPORT UNCLASSIFIED	18. SECURITY CLASSIFICATION ON THIS PAGE UNCLASSIFIED	19. SECURITY CLASSIFICATION OF ABSTRACT UNCLASSIFIED	20. LIMITATION OF ABSTRACT UL	

20030623 040

# From Nonlinear to Hamiltonian via Feedback<sup>1</sup>

Paulo Tabuada and George J. Pappas

Department of Electrical and Systems Engineering  
University of Pennsylvania  
Philadelphia, PA 19104  
e-mail: {tabuadap, pappasg}@seas.upenn.edu

## Abstract

Mechanical control systems are a very important class of nonlinear control systems. They possess a rich mathematical structure which can be extremely important for the solution of various control problems. In this paper, we expand the applicability of design methodologies developed for mechanical control systems by locally rendering nonlinear control systems, mechanical by a proper choice of feedback. In particular, we characterize control systems which can be transformed to Hamiltonian control systems by a local feedback transformation.

## 1 Introduction

Mechanical control systems are clearly a very large class of nonlinear control systems. Their refined mathematical structure of mechanical control systems can be extremely useful and must be exploited in their control design. It is therefore very natural that a wealth of powerful design methodologies have been developed for mechanical systems. Examples include energy shaping methods [4, 2, 12], specialized controllability notions and tests [9, 5], motion planning and generation [7], among many others. See also the monographs [11, 14] for several design techniques based on the related notion of passivity.

In this paper, we broaden the applicability of design tools for mechanical control systems to other classes of nonlinear control systems by proper choice of feedback. More specifically, we will solve the following equivalence problem: *Given a control system, determine if it is possible to transform it to a Hamiltonian control system by a feedback transformation.* We recall that this has been considered one of the open problems in the area of mechanical feedback control systems as described in the following passage from [3]: “Find other techniques which enable one to use feedback control for

*mechanical or, indeed, nonmechanical systems, which leave or put the system into Hamiltonian or Lagrangian form.”*

After reviewing some notions of symplectic geometry, in Section 2, we introduce a notion of Hamiltonian control systems. In Section 3 we provide a simple test to determine if a given control system can be rendered Hamiltonian with respect to a *given* Hamiltonian. In Section 4, we determine sufficient and necessary conditions for the existence of *any* Hamiltonian and a feedback transformation rendering a control system Hamiltonian. It should be noted that the feedback transformations are local in nature, and with respect to the canonical symplectic structure. These geometric conditions are then illustrated with an example. In Section 5 we present some topics for further research.

## 2 Hamiltonian Control Systems

Several different models of mechanical control systems abound in the literature on control of mechanical control systems. We will adopt what we think to be one of the simplest such models: Hamiltonian control systems. To introduce it, we review some elementary notions of symplectic geometry [6, 10]. A symplectic form  $\omega$  on a smooth manifold  $M$  is a two-form satisfying the following properties:

1. Nondegeneracy:  $\omega(X, Y) = 0$  for every  $X \in TM$  implies  $Y = 0$ ,
2. Closedness:  $d\omega = 0$ .

where we have denoted the exterior derivative by  $d$ . We also use the notation  $i_X\omega$  to represent the contraction of the two-form  $\omega$  with the vector field  $X$ , that is  $(i_X\omega)(Y) = \omega(X, Y)$  for any  $Y \in TM$ . The first property of the form  $\omega$  is required to obtain an isomorphism between  $TM$  and  $T^*M$  from  $\omega$ . This is achieved by the correspondence  $X \mapsto i_X\omega \in T^*M$  which allows to associate a unique Hamiltonian vector field  $X_H$  with

<sup>1</sup>This research is partially supported by the National Science Foundation Information Technology Research Grant CCR01-21431.

**DISTRIBUTION STATEMENT A**  
Approved for Public Release  
Distribution Unlimited

any smooth map  $H : M \rightarrow \mathbb{R}$  through the equality:

$$\mathbf{i}_{X_H}\omega = \mathbf{d}H$$

Hamiltonian vector fields conserve energy (the Hamiltonian  $H$ ) along their flows  $\phi_t$ . This fact can be shown by the following computation:

$$\begin{aligned} \frac{d}{dt}\phi_t^*H &= \phi_t^*(\mathcal{L}_{X_H}H) \\ &= \phi_t^*(\mathbf{d}H \cdot X_H) \\ &= \phi_t^*(\mathbf{i}_{X_H}\omega \cdot X_H) \\ &= \phi_t^*(\omega(X_H, X_H)) \\ &= 0 \end{aligned}$$

The nondegeneracy condition on  $\omega$  also implies that the dimension on  $M$  has to be an even number, see for example [6]. The closedness condition is required to ensure that the flow  $\phi_t$  of a Hamiltonian vector field  $X_H$  respects the symplectic form, that is  $\phi_t^*\omega = \omega$ , as can be seen again by simple computations where we denote by  $\mathcal{L}_{X_H}\omega$  the Lie derivative of  $\omega$  along  $X_H$ .

$$\begin{aligned} \frac{d}{dt}\phi_t^*\omega &= \phi_t^*(\mathcal{L}_{X_H}\omega) \\ &= \phi_t^*(\mathbf{d}\mathbf{i}_{X_H}\omega + \mathbf{i}_{X_H}\mathbf{d}\omega) \\ &= \phi_t^*(\mathbf{d}\mathbf{d}H + \mathbf{i}_{X_H}\mathbf{d}\omega) \\ &= \phi_t^*(\mathbf{i}_{X_H}\mathbf{d}\omega) \end{aligned}$$

We now introduce the class of Hamiltonian control systems we will use in this paper:

**Definition 2.1** Let  $M$  be a smooth manifold equipped with symplectic form  $\omega$  and let  $U$  be the input manifold. A control affine system  $F : M \times U \rightarrow TM$ :

$$F = X + \sum_{i=1}^p Y_i u_i$$

is said to be a Hamiltonian control system with Hamiltonian  $H$  if the vector field  $X$  is Hamiltonian with Hamiltonian  $H$ .

Within the context of Hamiltonian control systems one could also consider other models, for example, one could consider that the vector fields  $Y_i$  are also Hamiltonian [16] or even the more general class of port-controlled Hamiltonian systems [17]. However, we will focus on this simple model as the techniques developed in this paper extend to such cases in a straightforward manner.

### 3 Achieving a given Hamiltonian

We start by determining if there exists a feedback transformation, that is, a map<sup>1</sup>

<sup>1</sup>In the current setting where control systems are assumed to be affine in the inputs it is natural to restrict feedback transfor-

$\alpha(x) + \beta(x)v : M \times U \rightarrow U$  with  $\beta(x)$  invertible such that the feedback transformed system:

$$X(x) + \sum_i Y_i(x)\alpha_i(x) + \sum_{i,j} Y_i(x)\beta_{ij}(x)v_j \quad (3.1)$$

is Hamiltonian with a given Hamiltonian  $H$ . From expression (3.1) it is clear that one only needs to design  $\alpha(x)$  to change  $X$ , so we will simply consider that  $\beta(x)$  is the identity map on  $U$ . This question has the following simple answer:

**Proposition 3.1** Let  $F$  be an affine control system on a smooth manifold  $M$  equipped with symplectic form  $\omega$  and  $H : M \rightarrow \mathbb{R}$  a smooth map. There exists a local feedback transformation rendering  $F$  Hamiltonian with Hamiltonian  $H$  iff:

$$\mathbf{d}H - \mathbf{i}_X\omega \in \text{span}\{\mathbf{i}_{Y_1}\omega, \mathbf{i}_{Y_2}\omega, \dots, \mathbf{i}_{Y_p}\omega\} \quad (3.2)$$

or equivalently:

$$(\mathbf{d}H - \mathbf{i}_X\omega) \wedge \mathbf{i}_{Y_1}\omega \wedge \mathbf{i}_{Y_2}\omega \wedge \dots \wedge \mathbf{i}_{Y_p}\omega = 0$$

**Proof:** Assume that a such a feedback exists, then the feedback transformed system satisfies:

$$\mathbf{i}_{X+\sum_{i=1}^p \alpha_i(x)Y_i(x)}\omega = \mathbf{d}H$$

which we rewrite as:

$$\mathbf{d}H - \mathbf{i}_X\omega = \sum_{i=1}^p \alpha_i \mathbf{i}_{Y_i}\omega$$

clearly showing that (3.2) is satisfied. Conversely, assume that (3.2) holds, then there are locally defined smooth functions  $a_i : M \rightarrow \mathbb{R}$  such that:

$$\mathbf{d}H - \mathbf{i}_X\omega = \sum_{i=1}^p a_i \mathbf{i}_{Y_i}\omega$$

We now define  $\alpha$  by the equalities  $\alpha_i = -a_i$  which define the desired local feedback. ■

While the conditions in Proposition 3.1 provide a quick test to determine if one can transform a control system to a Hamiltonian one with a specified  $H$ , they are not useful if one wants to search for a feedback transformation and also a Hamiltonian. We devote the next section to this problem.

### 4 Achieving any Hamiltonian

To provide a solution for the general case where no Hamiltonian is a priori specified we will reshape condition (3.2). We start by making the following additional assumption:

mations to affine transformations as this ensures that the transformed system is still input affine.

1. The distribution spanned by the input vector fields  $Y_1, Y_2, \dots, Y_p$ , denoted by  $\Delta$ , is locally of constant rank.

#### 4.1 A Geometric Solution

To develop a geometric solution we introduce the symplectic orthogonal of  $\Delta$ , which we denote by  $\Delta^\omega$  and define by:

$$\Delta^\omega = \{Z \in TM : \omega(Z, Y) = 0 \quad \forall Y \in \Delta\}$$

Note that  $\Delta^\omega$  is locally of constant rank in virtue of nondegeneracy assumption and smoothness of  $\omega$ . By making use of  $\Delta^\omega$  we can reformulate condition (3.2) to a more useful form. If condition (3.2) is satisfied then  $dH - i_X\omega = \sum_{i=1}^p a_i i_{Y_i}\omega$  and contracting this expression with any vector field in  $\Delta^\omega$  we have:

$$dH(Z) = \omega(X, Z) \quad \forall Z \in \Delta^\omega \quad (4.1)$$

Conversely, if (4.1) is satisfied, then  $dH = i_X\omega + \gamma$  for some  $\gamma \in \text{span}\{i_{Y_1}\omega, i_{Y_2}\omega, \dots, i_{Y_p}\omega\}$  which implies condition (3.2) and shows how (3.2) can be equivalently expressed as (4.1). This expression can also be regarded as a partial differential equation (PDE) whose solution provides the desired Hamiltonian  $H$ . We now interpret this PDE geometrically by defining the new manifold:

$$\bar{M} = M \times \mathbb{R}$$

with local coordinates  $(x, y)$ , where  $x$  are coordinates for  $M$  and  $y$  coordinates for  $\mathbb{R}$ . We also define the map  $\bar{H} : \bar{M} \rightarrow \mathbb{R}$  by:

$$\bar{H}(x, y) = H(x) - y$$

as well as the vector fields:

$$\bar{Z} = Z \frac{\partial}{\partial x} + \omega(X, Z) \frac{\partial}{\partial y}$$

defining the distribution  $\bar{\Delta}^\omega$  on  $\bar{M}$ . These new objects allow to rewrite (4.1) as:

$$\mathcal{L}_{\bar{Z}} \bar{H} = 0 \quad \forall \bar{Z} \in \bar{\Delta}^\omega$$

which we interpret as the requirement that vector fields  $\bar{Z}$  are tangent to the submanifold  $(\bar{H})^{-1}(0)$  of  $\bar{M}$ . We thus see that, in this geometric interpretation of PDE (4.1), finding a Hamiltonian  $H$  is equivalent to finding a submanifold of  $\bar{M}$ , implicitly defined by a map  $\bar{H} : \bar{M} \rightarrow \mathbb{R}$ , such that  $\bar{\Delta}^\omega$  is contained in the tangent space of  $(\bar{H})^{-1}(0)$ . Furthermore  $\bar{H}$  must also satisfy  $\frac{\partial \bar{H}}{\partial y} \neq 0$  which ensures, via the implicit function theorem, that  $\bar{H}$  defines a function on  $M$ , the desired Hamiltonian  $H$ . Necessary and sufficient conditions for the local existence of such a map  $\bar{H}$  are given in the next result which provides geometric conditions for the integrability of PDE (4.1):

**Theorem 4.1** *Let  $F$  be an affine control system on a smooth manifold  $M$  with symplectic form  $\omega$  and denote by  $C$  and  $\bar{C}$  the involutive closures of  $\Delta^\omega$  and  $\bar{\Delta}^\omega$  which we assume to be regular. There exists a locally defined map  $H : M \rightarrow \mathbb{R}$  and a local feedback transformation rendering  $F$  Hamiltonian with Hamiltonian  $H$  iff:*

$$\dim(C) = \dim(\bar{C}) \quad (4.2)$$

**Proof:** In view of the discussion preceding Theorem 4.1 it suffices to show that (4.2) is sufficient and necessary for the existence of the map  $\bar{H} : \bar{M} \rightarrow \mathbb{R}$  satisfying  $\frac{\partial \bar{H}}{\partial y} \neq 0$  and  $\bar{\Delta}^\omega \subseteq T((\bar{H})^{-1}(0))$ . To show necessity assume the existence of  $\bar{H} = H - y$  satisfying  $\bar{\Delta}^\omega \subseteq T((\bar{H})^{-1}(0))$ . Let  $i : M \rightarrow \bar{M}$  be the map  $i(x) = (x, H(x))$  and note that:

$$\begin{aligned} T_x i \cdot Z(x) &= Z(x) \frac{\partial}{\partial x} + T_x H \cdot Z(x) \frac{\partial}{\partial y} \\ &= Z(x) \frac{\partial}{\partial x} + \omega(X, Z) \frac{\partial}{\partial y} \\ &= \bar{Z}(x, H(x)) \\ &= \bar{Z} \circ i(x) \end{aligned}$$

where the second equality follows from (4.1). This shows that the vector fields  $Z$  are  $i$ -related to the vector fields  $\bar{Z}$ . Since if  $Z_i$  is  $i$ -related to  $\bar{Z}_i$  and  $Z_j$  is  $i$ -related to  $\bar{Z}_j$ , the bracket  $[Z_i, Z_j]$  is  $i$ -related to  $[\bar{Z}_i, \bar{Z}_j]$  (see [1]), it follows by induction that  $\dim(C) = \dim(\bar{C})$ .

Sufficiency is proved by applying Frobenius theorem to  $\bar{C}$  (which is regular by assumption) to conclude the existence of a submanifold of  $\bar{M}$  to which the vector fields in  $\bar{\Delta}^\omega$  are tangent. Furthermore, Frobenius theorem also ensures that this submanifold is locally described by the zero level of a smooth map  $\bar{H} : \bar{M} \rightarrow \mathbb{R}$  [1]. It remains to show that  $\frac{\partial \bar{H}}{\partial y} \neq 0$ . We proceed by contradiction assuming that  $\dim(C) = \dim(\bar{C})$  and  $\frac{\partial \bar{H}}{\partial y} = 0$ . Then, the vector field  $\bar{Z} = 0 \frac{\partial}{\partial x} + 1 \frac{\partial}{\partial y} \in \ker(d\bar{H}) = \ker(\frac{\partial \bar{H}}{\partial x} dx + \frac{\partial \bar{H}}{\partial y} dy)$ . This shows that  $\dim(\bar{C})$  is at least greater than  $\dim(C)$  by one, a contradiction. ■

Theorem 4.1 gives necessary and sufficient conditions for the existence of a solution to PDE (4.1). The solution of partial differential equations naturally appear in similar local feedback equivalence problems, such as feedback linearization [8], and several control design problems for mechanical control systems [2, 12].

As an immediate consequence of Theorem 4.1 we see that in the case  $\dim(\Delta^\omega) = 1$ , that is, control system  $F$  has  $2m - 1$  inputs and  $\dim(M) = 2m$ , condition (4.2) is automatically satisfied.

**Corollary 4.2** *Let  $F$  be an affine control system on a smooth manifold  $M$  of dimension  $2m$  with symplectic*

form  $\omega$  and  $2m - 1$  inputs. Then, there exists a locally defined map  $H : M \rightarrow \mathbb{R}$  and a local feedback transformation rendering  $F$  Hamiltonian with Hamiltonian  $H$ .

The discussion so far has assumed that the symplectic form  $\omega$  has been a priori specified. However, this is not necessary in virtue of Darboux theorem [6] which asserts that, locally, every symplectic manifold of dimension  $2m$  is symplectomorphic (diffeomorphic by a diffeomorphism that preserves the symplectic forms) to  $\mathbb{R}^{2m}$  with symplectic form:

$$\omega = \sum_{i=1}^m dx_i \wedge dy_i \quad (4.3)$$

expressed in coordinates  $(x_1, x_2, \dots, x_m, y_1, y_2, \dots, y_m)$  for  $\mathbb{R}^{2m}$ . We thus see that if a control system can be locally rendered Hamiltonian with respect to the form  $\omega$ , then by a change of coordinates, it is also Hamiltonian with respect to any other symplectic form.

#### 4.2 An alternative Characterization

The conditions for the existence of a Hamiltonian and a feedback transformation given in Theorem 4.1 require the computation of several objects such as  $\Delta^\omega$ ,  $\overline{\Delta^\omega}$ ,  $\mathcal{C}$ ,  $\overline{\mathcal{C}}$ , etc. However, some of these objects contain some degree of redundancy and we will now see how one can verify the conditions of Theorem 4.1 in a more direct way. In particular we shall take advantage of the special form of the vector fields in  $\overline{\Delta^\omega}$ . From the expression of  $[\overline{Z}_i, \overline{Z}_j]$  in local coordinates:

$$[\overline{Z}_i, \overline{Z}_j] = \begin{bmatrix} \frac{\partial Z_j}{\partial x} & 0 \\ d\omega(X, Z_j) & 0 \end{bmatrix} \begin{bmatrix} Z_i \\ \omega(X, Z_i) \end{bmatrix} - \begin{bmatrix} \frac{\partial Z_i}{\partial x} & 0 \\ d\omega(X, Z_i) & 0 \end{bmatrix} \begin{bmatrix} Z_j \\ \omega(X, Z_j) \end{bmatrix}$$

we see that  $[\overline{Z}_i, \overline{Z}_j]$  is given by:

$$[Z_i, Z_j] \frac{\partial}{\partial x} + (\mathcal{L}_{Z_i} \omega(X, Z_j) - \mathcal{L}_{Z_j} \omega(X, Z_i)) \frac{\partial}{\partial y} \quad (4.4)$$

We now rewrite  $\mathcal{L}_{Z_i} \omega(X, Z_j) - \mathcal{L}_{Z_j} \omega(X, Z_i)$  as:

$$-d(\mathbf{i}_{Z_j} \mathbf{i}_X \omega)(Z_i) - \mathcal{L}_{Z_j} \omega(X, Z_i)$$

which by the Cartan magic formula [1] becomes:

$$\begin{aligned} & -(\mathcal{L}_{Z_j} \mathbf{i}_X \omega - \mathbf{i}_{Z_j} d\mathbf{i}_X \omega)(Z_i) - \mathcal{L}_{Z_j} \omega(X, Z_i) \\ &= -\mathbf{i}_{Z_i} \mathcal{L}_{Z_j} \mathbf{i}_X \omega + \mathbf{i}_{Z_i} \mathbf{i}_{Z_j} d\mathbf{i}_X \omega - \mathcal{L}_{Z_j} \omega(X, Z_i) \\ &= \mathcal{L}_{Z_j} \mathbf{i}_{Z_i} \mathbf{i}_X \omega - \mathbf{i}_{Z_i} \mathcal{L}_{Z_j} \mathbf{i}_X \omega + \mathbf{i}_{Z_i} \mathbf{i}_{Z_j} d\mathbf{i}_X \omega \\ &= \omega(X, [Z_i, Z_j]) + \mathbf{i}_{Z_i} \mathbf{i}_{Z_j} d\mathbf{i}_X \omega \end{aligned} \quad (4.5)$$

and where the last equality is a consequence of the fact that  $\mathcal{L}_{Z_j} \mathbf{i}_{Z_i} \gamma - \mathbf{i}_{Z_i} \mathcal{L}_{Z_j} \gamma = \gamma([Z_i, Z_j])$  for any one-form  $\gamma$ .

Expression (4.5) allows to formulate the following alternative version of Theorem 4.1:

#### Theorem 4.3 (Alternative Characterization)

Let  $F$  be an affine control system on a smooth manifold  $M$  with symplectic form  $\omega$ . There exists a locally defined map  $H : M \rightarrow \mathbb{R}$  and a local feedback transformation rendering  $F$  Hamiltonian with Hamiltonian  $H$  iff:

$$\mathbf{i}_{Z_i} \mathbf{i}_{Z_j} d\mathbf{i}_X \omega = 0 \quad \forall Z_i, Z_j \in \Delta^\omega \quad (4.6)$$

**Proof:** As we have seen in the proof of Theorem 4.1, existence of  $H$  and the feedback transformation implies that every vector field  $Z \in \Delta^\omega$  is  $i$ -related to the vector field  $\overline{Z} \in \overline{\Delta^\omega}$  for  $i(x) = (x, H(x))$ . This, in turn, implies that  $[Z_i, Z_j]$  is also  $i$ -related to  $[\overline{Z}_i, \overline{Z}_j]$  leading to:

$$[\overline{Z}_i, \overline{Z}_j] = [Z_i, Z_j] \frac{\partial}{\partial x} + \omega(X, [Z_i, Z_j]) \frac{\partial}{\partial y}$$

Comparing this expression with (4.4) we see that we necessarily have  $\mathbf{i}_{Z_i} \mathbf{i}_{Z_j} d\mathbf{i}_X \omega = 0$ .

To show sufficiency we note that if  $[Z_i, Z_j] = \sum_l a_l Z_l$  for  $Z_i, Z_j, Z_l \in \mathcal{C}$  and smooth real valued functions  $a_l$ , it follows by (4.4) that  $[\overline{Z}_i, \overline{Z}_j]$  equals:

$$\begin{aligned} & [Z_i, Z_j] \frac{\partial}{\partial x} + (\omega(X, [Z_i, Z_j]) + \mathbf{i}_{Z_i} \mathbf{i}_{Z_j} d\mathbf{i}_X \omega) \frac{\partial}{\partial y} \\ &= \sum_l a_l Z_l \frac{\partial}{\partial x} + (\omega(X, \sum_l a_l Z_l) + \mathbf{i}_{Z_i} \mathbf{i}_{Z_j} d\mathbf{i}_X \omega) \frac{\partial}{\partial y} \\ &= \sum_l a_l Z_l \frac{\partial}{\partial x} + (\sum_l a_l \omega(X, Z_l) + \mathbf{i}_{Z_i} \mathbf{i}_{Z_j} d\mathbf{i}_X \omega) \frac{\partial}{\partial y} \\ &= \sum_l a_l \overline{Z}_l + \mathbf{i}_{Z_i} \mathbf{i}_{Z_j} d\mathbf{i}_X \omega \frac{\partial}{\partial y} \end{aligned}$$

The assumption  $\mathbf{i}_{Z_i} \mathbf{i}_{Z_j} d\mathbf{i}_X \omega = 0$  now allows to conclude that  $[Z_i, Z_l] = \sum a_l Z_l \Rightarrow [\overline{Z}_i, \overline{Z}_l] = \sum a_l \overline{Z}_l$  and an induction argument shows that  $\dim(\mathcal{C}) = \dim(\overline{\mathcal{C}})$  which by Theorem 4.1 implies the existence of  $H$  and the desired feedback transformation. ■

This formulation also allows to see that Corollary 4.2 is a simple consequence of the skew-symmetry of  $\omega$ . If  $\dim(\Delta^\omega) = 1$  we have that for any  $Z_i, Z_j \in \Delta^\omega$ ,  $Z_i = \lambda Z_j$  for a smooth real valued map  $\lambda$  and  $(d\mathbf{i}_X \omega)(Z_i, \lambda Z_i) = \lambda(d\mathbf{i}_X \omega)(Z_i, Z_i) = 0$ .

The necessary steps to determine the existence of a solution to PDE (4.1) can now be resumed to the following:

1. Compute a basis for the symplectic orthogonal  $\Delta^\omega$  of  $\Delta$ ,  $\Delta^\omega = \{Z \in TM : \omega(Z, Y) = 0 \quad \forall Y \in \Delta\}$ ,
2. Check if  $\mathbf{i}_{Z_i} \mathbf{i}_{Z_j} d\mathbf{i}_X \omega = 0$  for every  $Z_i, Z_j$  in the basis of  $\Delta^\omega$  computed in step 1.

If Theorem 4.1 is satisfied, then a solution to (4.1) must be obtained in order to determine the feedback transformation. If  $H$  is such a solution, we determine the feedback transformation by computing the smooth functions  $a_i$  satisfying:

$$dH - i_X \omega = \sum_{i=1}^p a_i i_{Y_i} \omega$$

These functions allow to determine the term  $\alpha(x)$  of the feedback transformation  $\alpha(x) + \beta(x)v$  by the equalities  $\alpha_i = -a_i$ . The term  $\beta(x)$  can be taken as the identity on  $U$  or any other invertible (pointwise) linear map from  $U$  to  $U$ .

### 4.3 Example

We now provide an example of the previously introduced methodology. Consider the following control system:

$$\begin{aligned}\dot{x}_1 &= x_2 x_3 + x_2 u_1 \\ \dot{x}_2 &= x_1 x_2^2 + \frac{1}{2} x_3^2 \\ \dot{x}_3 &= x_1 x_2 x_4 + x_2 x_3 u_2 \\ \dot{x}_4 &= x_1 x_3\end{aligned}\quad (4.7)$$

on  $\mathbb{R}^4$  with symplectic form  $\omega = dx_1 \wedge dx_2 + dx_3 \wedge dx_4$ . In this case we have:

$$X = \begin{bmatrix} x_2 x_3 \\ x_1 x_2^2 + \frac{1}{2} x_3^2 \\ x_1 x_2 x_4 \\ x_1 x_3 \end{bmatrix} \quad Y_1 = \begin{bmatrix} x_2 \\ 0 \\ 0 \\ 0 \end{bmatrix} \quad Y_2 = \begin{bmatrix} 0 \\ 0 \\ x_2 x_3 \\ 0 \end{bmatrix} \quad (4.8)$$

and  $\Delta = \text{span}\{Y_1, Y_2\}$ . We now follow the steps outlined in the previous section computing:

1. The symplectic orthogonal of  $\Delta$  is obtained by first computing:

$$\begin{aligned}i_{Y_1} \omega &= x_2 dx_2 \\ i_{Y_2} \omega &= x_2 x_3 dx_4\end{aligned}\quad (4.9)$$

and then determining  $\Delta^\omega$  as the annihilating distribution of  $\text{span}\{i_{Y_1} \omega, i_{Y_2} \omega\}$ . Distribution  $\Delta^\omega$  is then given by the span of:

$$Z_1 = \begin{bmatrix} 1 \\ 0 \\ 0 \\ 0 \end{bmatrix} \quad Z_2 = \begin{bmatrix} 0 \\ 0 \\ 1 \\ 0 \end{bmatrix} \quad (4.10)$$

2. We now compute:

$$\begin{aligned}i_X \omega &= -\left(\frac{1}{2} x_3^2 + x_1 x_2^2\right) dx_1 + x_2 x_3 dx_2 \\ &\quad - x_1 x_3 dx_3 + x_1 x_2 x_4 dx_4\end{aligned}$$

which by differentiation gives:

$$\begin{aligned}di_X \omega &= -2x_1 x_2 dx_2 \wedge dx_1 - x_3 dx_3 \wedge dx_1 \\ &\quad + x_2 dx_3 \wedge dx_2 - x_3 dx_1 \wedge dx_3 \\ &\quad + x_2 x_4 dx_1 \wedge dx_4 + x_1 x_4 dx_2 \wedge dx_4 \\ &= -2x_1 x_2 dx_2 \wedge dx_1 + x_2 dx_3 \wedge dx_2 \\ &\quad + x_2 x_4 dx_1 \wedge dx_4 + x_1 x_4 dx_2 \wedge dx_4\end{aligned}$$

and evaluating  $di_X \omega$  on  $Z_1$  and  $Z_2$ :

$$\begin{aligned}i_{Z_2} di_X \omega &= x_2 dx_2 \\ i_{Z_1} i_{Z_2} di_X \omega &= 0\end{aligned}$$

shows, via Theorem 4.3, that a Hamiltonian and a feedback transformation exist.

To obtain  $H$  one has to solve (4.1), which in this case results in:

$$\begin{aligned}\frac{\partial H}{\partial x_1} &= -\frac{1}{2} x_3^2 - x_1 x_2^2 \\ \frac{\partial H}{\partial x_3} &= -x_1 x_3\end{aligned}$$

It suffices to solve the first equation to obtain:

$$H = -\frac{1}{2}(x_1^2 x_2^2 + x_1 x_3^2)$$

One now computes  $dH - i_X \omega = (x_1^2 x_2 - x_2 x_3) dx_2 - x_1 x_2 x_4 dx_4$  which can be written as  $dH - i_X \omega = a_1 i_{Y_1} \omega + a_2 i_{Y_2} \omega$  for:

$$a_1 = (x_3 - x_1^2) \quad a_2 = -\frac{1}{x_3} x_1 x_4 \quad (4.11)$$

These functions now allow to define the feedback transformation as  $\alpha_i(x) = -a_i(x)$  and for  $\beta(x)$  we simply use the identity on  $U$ . The feedback transformed system is now of the form:

$$\begin{aligned}\dot{x}_1 &= \frac{\partial H}{\partial x_2} + x_2 u_1 \\ \dot{x}_2 &= -\frac{\partial H}{\partial x_1} \\ \dot{x}_3 &= \frac{\partial H}{\partial x_4} + x_2 x_3 u_2 \\ \dot{x}_4 &= -\frac{\partial H}{\partial x_3}\end{aligned}$$

revealing its Hamiltonian structure.

## 5 Conclusions

In this paper, we have addressed the problem of rendering a nonlinear control system Hamiltonian by a proper choice of feedback. We showed that the solution is given by the solution of a partial differential

equation, and provided sufficient and necessary conditions for the local existence of solutions. These results enlarge the class of systems to which powerful control design methods developed for mechanical systems are applicable.

Many related problems remain open. When we cannot perform such a feedback transformation it may still be possible to extract a quotient (an abstraction, see for example [13, 15]) or a subsystem that is mechanical, or that can be rendered mechanical by feedback. This would allow to synthesize controllers for part of the variables by making use of techniques developed for mechanical control systems. Another alternative is to perform a change of coordinates on the state space that would render the system Hamiltonian, possibly complemented by a feedback transformation.

### References

- [1] R. Abraham, J. Marsden, and T. Ratiu. *Manifolds, Tensor Analysis and Applications*. Applied Mathematical Sciences. Springer-Verlag, 1988.
- [2] A. M. Bloch, D. Chang, and J. E. Marsden N. E. Leonard. Controlled Lagrangians and the stabilization of mechanical systems II: Potential shaping. *IEEE Transactions on Automatics Control*, 46(10):1556–1571, October 2001.
- [3] A. M. Bloch, N. E. Leonard, and J. E. Marsden. Mechanical feedback control systems. In Vincent D. Blondel, Eduardo D. Sontag, M. Vidyasagar, and Jan C. Willems, editors, *Open Problems in Mathematical Systems and Control Theory*, pages 39–44. Springer-Verlag, London, 1999.
- [4] A. M. Bloch and J. E. Marsden N. E. Leonard. Controlled Lagrangians and the stabilization of mechanical systems I: The first matching theorem. *IEEE Transactions on Automatics Control*, 45(12):2253–2270, December 2000.
- [5] Francesco Bullo and Kevin M. Lynch. Kinematic controllability for decoupled trajectory planning in underactuated mechanical systems. *IEEE Transactions on Robotics and Automation*, 17(4):402–412, August 2001.
- [6] Ana Cannas da Silva. *Lectures on Symplectic Geometry*, volume 1764 of *Lecture Notes in Mathematics*. Springer-Verlag, 2001.
- [7] A. D. Lewis F. Bullo, N. E. Leonard. Controllability and motion algorithms for underactuated Lagrangian systems on lie groups. *IEEE Transactions on Automatic Control*, 45(8):1437–1454, 2000.
- [8] Alberto Isidori. *Nonlinear Control Systems*. Springer-Verlag, third edition, 1996.
- [9] Andrew Lewis and Richard M. Murray. Configuration controllability of simple mechanical control systems. *SIAM Journal on Control and Optimization*, 35(3):766–790, May 1997.
- [10] Jerrold E. Marsden and Tudor S. Ratiu. *Introduction to Mechanics and Symmetry*. Texts in Applied Mathematics. Springer-Verlag, 1999.
- [11] Romeo Ortega and Per Johan Nicklasson. *Passivity-Based control of Euler-Lagrange Systems*. Communications and Control Engineering. Springer-Verlag, New York, October 1998.
- [12] Romeo Ortega, Arjan van der Schaft, Bernhard Maschke, and Gerardo Escobar. Interconnection and damping assignment passivity-based control of port-controlled Hamiltonian systems. *Automatica*, 38(4):585–596, April 2002.
- [13] George J. Pappas and Slobodan Simic. Consistent hierarchies of affine nonlinear systems. *IEEE Transactions on Automatic Control*, 47(5):745–756, 2002.
- [14] R. Sepulchre, M. Jankovic, and Petar V. Kokotovic. *Constructive Nonlinear Control*. Communications and Control Engineering. Springer-Verlag, New York, January 1997.
- [15] Paulo Tabuada and George J. Pappas. Abstractions of Hamiltonian control systems. *Automatica*, 2002. Submitted, available at [www.seas.upenn.edu/~tabuadap](http://www.seas.upenn.edu/~tabuadap).
- [16] A. J. van der Schaft. Hamiltonian dynamics with external forces and observations. *Mathematical Systems Theory*, 15:145–168, 1982.
- [17] Arjan van der Schaft. *L<sub>2</sub>-Gain and Passivity Techniques in Nonlinear Control*, volume 218 of *Lecture Notes in Control and Information Sciences*. Springer-Verlag, London, 1996.